


XACB085

empty pendant control station XAC-B - 8
vertical openings



Main

| | |
|-----------------------------|---|
| Range of product | Harmony XAC |
| Product or component type | Pendant control station |
| Control station name | XACB |
| Control station type | Double insulated |
| Enclosure material | Glass reinforced polyester |
| Electrical circuit type | Control circuit Power circuit |
| Enclosure type | Empty enclosure |
| Number of cut-out | 8 cut-outs |
| Cable entry | Rubber sleeve with stepped entry , cable outer diameter: 22...35 mm |
| Guard rail | Without |
| Cutout in base of enclosure | Without |

Complementary

| | |
|----------------------------------|----------------|
| Control station colour | Yellow |
| Vertical operator cut-out centre | 40 mm |
| Mechanical durability | 1000000 cycles |
| Product weight | 1.53 kg |

Environment

| | |
|--|---|
| Standards | CSA C22-2 No 14 EN/IEC 60947-5-1 UL 508 |
| Product certifications | CSA type 4 |
| Protective treatment | TH |
| Ambient air temperature for operation | -25...70 °C |
| Ambient air temperature for storage | -40...70 °C |
| Vibration resistance | 15 gn (f = 10...500 Hz) conforming to IEC 60068-2-6 |
| Shock resistance | 100 gn conforming to IEC 60068-2-27 |
| Class of protection against electric shock | Class II conforming to IEC 61140 |
| IP degree of protection | IP65 conforming to IEC 60529 |
| IK degree of protection | IK08 conforming to EN 50102 |
| RoHS EUR conformity date | 2Q2009 |
| RoHS EUR status | Will be compliant |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.