

Accessory for strips 3NJ41 In-line fuse switch disconnectors Sz. NH1-3 Current transformers can be integrated 150/1 A, Cl. 0.5



Figure similar

Model	
product brand name	SENTRON
product designation	Current transformer
design of the product	accessory for fuse switch disconnector 3NJ41
operating voltage	0.72 kV
insulation voltage rated value	3 kV
designation of overcurrent limiting factor	FS 5
current	
• at input rated value	150 A
value range of the operating frequency	50/60 Hz
Protection class	
protection class IP	IP20
Mechanical Design	
height	80 mm
width	52 mm
depth	26 mm
Net Weight	218 g
Environmental conditions	
ambient temperature during operation	
• minimum	-10 °C
• maximum	55 °C
Approvals Certificates	
Environment	General Product Approval

[Environmental Conformations](#)



Further information

Information on the packaging
<https://support.industry.siemens.com/cs/ww/en/view/109813875>
 Information for data generation and storage
<https://support.industry.siemens.com/cs/ww/en/view/109995012>
 Information- and Downloadcenter (Catalogs, Brochures,...)
<https://www.siemens.com/lowvoltage/catalogs>
 Industry Mall (Online ordering system)
<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3NJ4915-2FA10>
 Service&Support (Manuals, Certificates, Characteristics, FAQs,...)
<https://support.industry.siemens.com/cs/ww/en/ps/3NJ4915-2FA10>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

https://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3NJ4915-2FA10

CAX-Online-Generator

<https://www.siemens.com/cax>

Tender specifications

<https://www.siemens.com/specifications>

Characteristic curves

[https://curves.simaris.siemens.com/curves/<mmp_prod_noCOMP="HAUPT"></mmp_prod_no>](https://curves.simaris.siemens.com/curves/<mmp_prod_noCOMP=)

last modified:

6/13/2025 

